Introduction

The FSC-1071 is a 16ch Digital Input field wiring din rail mounting termination module which has indicating fuse blown fuseholders suitable for fitting the Bussmann GMT range of fuses. The fuse protects against sensor short circuit and provides the sensor power. The module also provides an Alarm signal to the PLC/controller in the event that a fuse has blown.An on board LED illuminates in the event that an alarm is present. Modules are available for 12, 24 & 48Vdc supplies. The module is supplied without fuses fitted as these are purchased separately.

Applications

Designed for use in large multi IO installations as found in Power stations and process plant, fuse failure indication makes plant maintenance quicker ensuring the customer can get up and working again with minimum delay. The alarm signal can be connected to a plc or DCS input which in turn can flag an alarm on a SCADA system directing maintenance to an identifiable input signal.

General Ratings

Storage temperature	-20 to +70 °C
Operating temperature	0 to 85 °C
Humidity	10-95% RH (non-condensing)
Dimensions	167mm width (Along Din Rail)
	90mm depth (Across Din Rail)
	62mm height
Voltage rating	Up to 60Vdc
Sensor supplyCurrent	16A max
Unit mounting	The unit can be mounted on all standard NS32 and NS35 DIN rail profiles to EN50 045, EN50 035 and EN50 022 standards
Connections to field inputs	Rising Clamp Screw terminals type MKDS 3/3 Connection capacity details are as follows Solid wire 0.2 - 4 mm2 Stranded wire 0.2 - 2.5 mm2 Stranded wire with ferrules fitted 0.25 - 2.5 mm2
Connection to PLC/DCs	Either 20 way IDC header or 2 part screw terminals

Colter Products Ltd.

FSC1074-24Vdc version shown above. Note that IDC connections match Schneider Advantys STB

GMT Fuses are purchased separately
we recommend GMT-1/4A,1/2A or 1A for
this module type.

Order Codes
FSC1071-12Vdc
FSC1071- 24Vdc
FSC1071- 48Vdc

Special options can be supplied such as reverse
RHS variant different connection options etc
Consult sales@coltergroup.co.uk for a quotation

COLTER GROUP
COLTER PRODUCTS LIMITED
UNIT 7, ZONE C
CHELMSFORD ROAD INDUSTRIAL ESTATE
DUNMOW
ESSEX
CM6 1HD

Telephone: + 44 (0)1371 876887
Fax: + 44 (0)1371 875638

E-Mail: sales@coltergroup.co.uk
Web Site: www.coltergroup.co.uk

© Copyright 2009

The unit described on this datasheet is designed and manufactured in Great Britain by Colter Products Ltd.
Colter Products reserve the right to amend these specifications and the user is asked to check the validity of the datasheet prior to use

FSC-1071 16DI-LHS 16ch Digital Input module

*Colter
Products
Ltd.*